

# MODEL 6126

## SINGLE ZONE BURGLARY CONTROL

### SPECIFICATIONS

#### **POWER**

**INPUT:** 12 VAC, CLASS 2, PLUG-IN TRANSFORMER, *TRANSFORMER SUPPLIED*

**STAND-BY:** 12 VOLT SEALED LEAD ACID BATTERY, 4 A.H. CAPACITY, *BATTERY NOT SUPPLIED*

#### **OUTPUTS**

**BELL/SIREN:** 12 VDC, 2.5 AMPERES

**DRY CONTACTS:** S.P.S.T. , NORMALLY-OPEN RATED 5 AMPERES @ 28 VDC OR 120 VAC

**REGULATED VOLTAGE:** 13.8 VDC, 300 MA., FILTERED

#### **KEYSWITCH**

MAINTAINED CONTACT TYPE, ROUND OR FLAT KEY, *KEYSWITCH NOT SUPPLIED*

#### **REMOTE LEDS**

**ARMED LED:** RED

**SECURE LED:** GREEN

CONTROL WILL ACCEPT UP TO THREE LED REMOTE STATIONS

#### **ADJUSTABLE BELL CUT-OFF**

**AUTO RESTORE TIME:** 2 TO 15 MINUTES

#### **INPUTS**

**OPEN CIRCUIT INSTANT LOOP**

**CLOSED CIRCUIT INSTANT LOOP:** MAXIMUM LOOP RESISTANCE 1000 OHMS

**24 HOUR LATCHING PANIC CIRCUIT:** OPEN CIRCUIT, (RESETS WITH ARMING KEYSWITCH)

#### **CABINET**

BEIGE FINISH, KNOCKOUT FOR OPTIONAL CAMLOCK, KNOCKOUT FOR CABINET MOUNTED KEYSWITCH, SECURE LED, FIVE ADDITIONAL KNOCKOUTS

#### **DIMENSIONS**

HEIGHT 11" , WIDTH 9" , DEPTH 3"

## ALARM CONTROLS CORPORATION

*"QUALITY SECURITY EQUIPMENT SINCE 1971"*

19 BRANDYWINE DRIVE, P.O. BOX 280, DEER PARK, NEW YORK 11729

1 800 645-5538 631 586-4220 FAX 631 586-6500

EMAIL: [INFO@ALARMCONTROLS.COM](mailto:INFO@ALARMCONTROLS.COM) [WWW.ALARMCONTROLS.COM](http://WWW.ALARMCONTROLS.COM)